

REMARKS

Favorable reconsideration and allowance of the subject application are respectfully requested. Claims 1-9 are pending in the present application, with claims 1 and 9 being independent.

Drawings

Applicant respectfully requests that the Examiner indicate in any subsequent Office Action, whether or not the drawing that was filed on August 23, 2004, has been accepted (see item 10 of the Office Action Summary Sheet).

In addition, Applicant submits herewith two additional figures in an effort to clarify the feature of sensor drift. These figures do not add any new subject matter.

Claim Rejections Under 35 U.S.C. §112

The Examiner rejected claims 1, 4-6, and 9 under 35 U.S.C. §112, first paragraph, as failing to comply with the written description requirement. This rejection is respectfully traversed.

Specifically, the Examiner states that Applicant expand on the meaning of "drift in the feedback sensor" and "forgetting factor" in the specification.

Applicant notes, that although the 35 U.S.C. §112, first paragraph, rejection is improper, because the features of sensor drift and forgetting factor are well known to one skilled in the

art, Applicant has amended the specification to explain these well known features in an effort expedite the prosecution of the present application.

Accordingly, withdrawal of the rejection is respectfully requested.

Substitute Specification

Applicant submits herewith a substitute specification, in which the specification has been amended, as noted above, in an effort to clarify the well-known features of sensor drift and forgetting factor.

Applicant respectfully submits that the substitute specification does not add any new subject matter.

Claim Rejections Under 35 U.S.C. §103

The Examiner rejected claims 1-3 and 7-9 under 35 U.S.C. §103(a) as being unpatentable over *Murakami et al.* (US 4,914,365) in view of *Hakala et al.* (WO 99/28229). This rejection is respectfully traversed.

Independent claim 1 is directed to a method for correcting speed feedback in a synchronous permanent-magnet motor. A speed value of the synchronous permanent-magnet motor is measured by a feedback sensor. Then, averages of a speed reference and a speed measurement are calculated for downward and upward constant-speed

travel. Gain and zero factors are identified and the measured speed value is corrected to compensate for drift in the feedback sensor.

Applicant respectfully submits that neither *Murakami et al.* nor *Hakala et al.* teach or suggest that a drift is compensated in a feedback sensor or a measuring unit, as recited in claims 1 and 9, respectively.

In fact, in rejecting independent claims 1 and 9, the Examiner failed to take these features into consideration. And thus, because the cited art, either alone or in combination, fails to teach or suggest all the features of the independent claims, a *prima facie* case of obviousness cannot be substantiated.

Furthermore, Applicant notes that *Murakami et al.* describes a servo motor controller for robots for compensating vibrations of the robot arm when running the robot with different speeds, loads etc. *Murakami et al.* does not teach, as noted above, how to compensate drift errors of the speed sensor output signal (ω_m -signal), because the uncompensated ω_m -signal is connected to the point 9 and to the box 11 (damper element) directly without any drift compensation, see Fig. 1 of *Murakami et al.* Thus, *Murakami et al.* does not teach offset drift compensation nor how to compensate gain drift of the ω_m -signal.

Dependent claims 2-8 should be considered allowable at least for depending from an allowable base claim.

Accordingly, withdrawal of the rejection is respectfully

requested.

Conclusion

In view of the above amendments and remarks, this application appears to be in condition for allowance and the Examiner is, therefore, requested to reexamine the application and pass the claims to issue.

Should there be any outstanding matters that need to be resolved in the present application, the Examiner is respectfully requested to contact Martin Geissler (Reg. 51,011) at telephone number (703) 205-8000, which is located in the Washington, DC area.

If necessary, the Commissioner is hereby authorized in this, concurrent, and future replies, to charge payment or credit any overpayment to Deposit Account No. 02-2448 for any additional fees required under 37 C.F.R. §§ 1.16 or 1.17; particularly, extension of time fees.

Respectfully submitted,

BIRCH, STEWART, KOLASCH & BIRCH, LLP

By

Michael K. Mutter, Reg.#29,680

P.O. Box 747

Falls Church, VA 22040-0747

(703) 205-8000

1381-0307P
MKM/MRG:tm

Attachment: Substitute Specification
 Marked-Up Version
 Additional Drawing (Figs. 3a and 3b)

AMENDMENTS TO THE SPECIFICATION

IN THE SPECIFICATION

Please replace the specification currently on record with the substitute specification submitted herewith.

AMENDMENTS TO THE DRAWINGS

Submitted herewith is one (1) additional drawing that complies with the provisions of 37 C.F.R. § 1.84. With the drawing, Figs. 3a and 3b have been added.

It is respectfully requested that the additional drawing be approved and made a part of the record of the above-identified application.

MARKED-UP VERSION OF THE FIRST SUBSTITUTE SPECIFICATION

Method For Correcting Speed Feedback In A Permanent-Magnet Motor

[0001] This application is a Continuation of copending PCT International Application No. PCT/FI02/00650 filed on July 31, 2002, which designated the United States, and on which priority is claimed under 35 U.S.C. § 120, and this Nonprovisional application claims priority under 35 U.S.C. § 119(a) on Patent Application No(s). 20011598 filed in Finland on August 1, 2001, the entire contents of which are hereby incorporated by reference.

BACKGROUND OF THE INVENTION

1. Field of the Invention

[0002] The present invention relates to a method for correcting speed feedback in a synchronous permanent-magnet motor.

2. Description of the Background Art

[0003] The problem is that, in the prior art, speed feedback in a synchronous permanent-magnet motor changes slowly e.g. as a function of temperature. When used as an elevator drive machine, the permanent-magnet motor is typically subjected to long-lasting peak-level loads, during which the temperature of the elevator machine rises. As the machine is developing heat, the speed feedback sensor attached to the machine becomes heated. In the present context, the above-mentioned speed feedback sensor is a tachometer. Thus, the speed information obtained from the tachometer changes, e.g. drifts, as a function of the temperature of the machine and especially of the tachometer. In the above-mentioned situation, the speed feedback information typically includes a 3% gain and zero error, which is visible in the entire speed regulation system. A rise in the machine temperature may naturally also be due to development of heat

in the elevator shaft when a synchronous permanent-magnet motor is used as an elevator drive motor.

[0004] Sensor drift is well known to mean that a sensor output has some error value that varies (drifts) for some reasons, e.g. time, temperature, utilization etc. Figs. 3a and 3b show an effect of offset drift and gain drift on a sensor output signal. In case of tachometers, offset drift and gain drift are caused, for example, when temperature changes because effective mechanical dimensions of tachometer changes causing drift in output signal, or effective magnetic fields inside tachometer changes causing drift in output signal. Offset drift and gain drift are also caused, for example, when using a tachometer (after installation) because tachometers have brushes (like DC motors), which will wear (mechanically) the more the tachometer is used. Wearing causes changes in electrical contacts and therefore, there will also be a drift in tachometer output signal. If the tachometer is not used regularly, contact elements will become oxidized causing drift. Such wearing effects may take weeks, months, even years in regular elevator use.

[0005] When using the tachometer as a servomotor feedback sensor, for example, in elevator systems, there may be up to a 10% error (drift) in a tachometer output signal, mainly because of tachometer gain drift. Both offset drift and gain drift may increase or decrease the tachometer signal (positive or negative drift), this behavior depends on tachometer constructions, manufacturing processes, usage etc. If drift errors are not compensated, the elevator may run slower than designed, it will have problems for stopping at floor stops, there may be oscillations in an elevator drive motor rotation speed, etc.

[0006] Previously known solutions attempted in order to deal with the above-mentioned problem by generating an advance estimate of the speed signal error produced in the above-described manner and eliminating the error on an

average. However, this method would not lead to accurate and reliable correction of the error.

[0005 0007] Another known way of solving the aforesaid problem is based on measurement of speed feedback. In this case, a known distance is traversed at a known speed, so the speed feedback error can be corrected at the operating point in question. The problem with this method is the continuously changing operating point, so the correction is naturally inaccurate.

SUMMARY OF THE INVENTION

[0006 0008] It is therefore an object of the present invention to eliminate the abovementioned drawback in static correction of speed feedback.

[0007 0009] A specific object of the invention is to disclose a method for continuous correction of speed feedback in a synchronous permanent-magnet motor that is better than prior-art methods.

[0008 0010] The method of the invention provides significant advantages as compared with prior art.

[0009 0011] The method of the invention allows advantageous correction of non-linearities in the measurement of the speed of a synchronous permanent-magnet motor. A specific object of the invention is to correct the slow drift of speed feedback in the measurement of the speed of a synchronous permanent-magnet motor. This aforesaid drift may occur e.g. in relation to temperature.

[0010 0012] Another advantage of the method of the invention is that it is an adaptive method, which means that, once the initial values have been set, the method learns the correct factors. In addition, in the calculation of the parameters to be used in the method, it is possible to include a forgetting factor, which makes it possible to perform the changing of the aforesaid parameters in a controlled

manner. Via controlled changing of the above-mentioned parameters, it is possible to achieve some correction of the direction dependence of the zero and gain error.

[0014 0013] The present invention concerns a method for correcting speed feedback in a synchronous permanent-magnet motor. In the most preferred embodiment of the invention, the averages of speed reference and speed measurement for constant-speed downward travel are calculated. In a corresponding manner, the average of speed reference and speed measurement for constant-speed upward travel is calculated. Next, the gain and zero factors to be used in the calculation are identified and the measured speed measurement value is corrected to the correct value.

[0012 0014] All the above-mentioned averages of speeds are calculated using the sum of the respective speeds and the number of samples. For example, the average of the speeds of downward constant-speed travel is calculated by dividing the sum of the speeds of constant-speed downward travel by the number of samples of downward constant speed. Similarly, the average of the speeds of constant-speed upward travel is calculated by dividing the sum of the speeds of constant-speed upward travel by the number of samples of upward constant speed.

[0013 0015] In a preferred embodiment of, the invention, the synchronous permanent-magnet motor of the method is used as an elevator drive machine.

[0014 0016] According to the method, the speed gain factor and the speed zero factor are first assigned certain initial values. After this, new speed gain and zero factors are calculated.

[0015 0017] According to the invention, the aforesaid speed gain factor and speed zero factor are updated by a forgetting factor. This aforesaid forgetting factor is an exponential factor. This aforesaid forgetting factor is used in the

present method so that, by applying the aforesaid forgetting factor, measurement samples of recent history are given more weight as compared with earlier measurement samples.

[0018] This forgetting factor is a weighting coefficient that defines how much old data and how much new data is used for calculating a new value for, for example, a tachometer gain factor or zero factor. For example, when calculating the gain factor, the following formula can be utilized:

$$G_n = K * MG_n + (1-K) * G_{n-1}$$

wherein G_n is the n th tachometer gain factor (calculated); MG_n is the n th measured tachometer gain factor (e.g., new measured sample); G_{n-1} is the previous tachometer gain factor (calculated); and K is the forgetting factor, which can have a value between 0 and 1, for example.

[0019] As such, for example, if $K = 0.1$, then 90 percent of the previous data is taken into account and 10 percent of the previous data is forgotten. In other words, by expanding the calculation of G_0 , G_1 , etc., the following exponential formulas could be produced:

$$G_0 = K * MG_0 \text{ (initial)}$$

$$G_1 = K * MG_1 + (1-K) * G_0$$

$$G_2 = K * MG_2 + (1-k) * G_1$$

[0020] Then, via substitution, one can see that G_2 would be $K * MG_2 + (1-k) * K * MG_1 + (1-K)^2 * K * MG_0$.

[0021] As can be seen in the above formulas, the older the measured value MG_n is, the smaller its weighting coefficient (forgetting factor) becomes, i.e., the history will be slowly forgotten.

[0022{0046}] Further scope of applicability of the present invention will become apparent from the detailed description given hereinafter. However, it should be understood that the detailed description and specific examples, while

indicating preferred embodiments of the invention, are given by way of illustration only, since various changes and modifications within the spirit and scope of the invention will become apparent to those skilled in the art from this detailed description.

BRIEF DESCRIPTION OF THE DRAWINGS

[0017 0023] The present invention will become more fully understood from the detailed description given hereinbelow and the accompanying drawings which are given by way of illustration only, and thus, are not limitive of the present invention, and wherein:

[0018 0024] Fig. 1 is an illustrative cross-section of a permanent magnet motor; and

[0019 0025] Fig. 2 is a flow chart of a method according to a preferred embodiment of the present invention; and

[0026] **Figs. 3a and 3b show an effect of offset drift and gain drift on a sensor output signal.**

DETAILED DESCRIPTION

[0020 0027] Fig. 1 shows a simplified illustration of a permanent magnet motor 1. The permanent magnet motor 1 has a shaft 3 that is fixedly attached to a rotor 5. The rotor 5 is typically a magnet that rotates because of an electrical force generated by windings of a stator 7. The permanent magnet motor 1 also further includes a speed feedback sensor 9 that measures a rotational speed of the permanent magnet motor 1. This speed feedback sensor 9 is shown to be located on the shaft 3 in Fig. 1, however, the speed feedback sensor 9 can also be provided in any suitable location on the permanent magnet motor 1.

[0021 0028] Fig. 2 is a flow chart of a method according to a preferred embodiment of the present invention. In step S1 averages of a speed reference and speed measurement for downward travel is calculated. In step S3 averages of a speed reference and speed measurement for upward travel is calculated. Then, in step S5, the gain and zero factors are identified. Thereafter, in step S7, the measured speed measurement value is corrected on the basis of the identified gain and zero factors.

[0022 0029] The invention being thus described, it will be obvious that the same may be varied in many ways. Such variations are not to be regarded as a departure from the spirit and scope of the invention, and all such modifications as would be obvious to one skilled in the art are to be included within the scope of the following claims.

What is claimed is: